

Cp	Wind Speed	Turbine Power 300W	RPM	AC voltage	AC current
0	0	0	0	0	0,00
0	1	0	46	8	0,00
0	2	0	92	16	0,00
0	3	0	137	24	0,00
0,18	4	9	183	32	0,28
0,265	5	26	229	40	0,65
0,305	6	51	275	48	1,07
0,335	7	89	321	56	1,60
0,345	8	137	366	63	2,16
0,371	9	210	412	71	2,94
0,376	10	292	458	79	3,68
0,384	11	397	504	87	4,54
0,402	12	539	550	95	5,66
0,41	13	600	550	95	6,29
0,412	14	600	550	95	6,29
0,412	15	600	550	95	6,29
0,412	16	600	550	95	6,29
0,412	17	600	550	95	6,29
0,412	18	600	550	95	6,29
0,412	19	600	550	95	6,29
0,412	20	600	550	95	6,29
0,412	21	600	550	95	6,29
0,412	22	600	550	95	6,29
0,412	23	600	550	95	6,29
0,412	24	600	550	95	6,29
0,412	25	600	550	95	6,29

